

Temposonics®

Magnetostrictive Linear Position Sensors

Temposonics® G-Series

Brief Instructions



Temposonics® G-Series

Brief Instructions

Table of contents

1. Introduction	3
2. Safety instructions	4
2.1 Intended use.....	4
2.2 Forseeable misuse.....	4
2.3 Installation, commissioning and operation.....	5
2.4 Safety instructions for use in explosion-hazardous areas.....	5
2.5 Warranty.....	5
2.6 Return.....	5
2.7 Maintenance & removal.....	5
3. Identification	6
3.1 Temposonics® G-Series GP.....	6
3.2 Temposonics® G-Series GH.....	6
3.3 Temposonics® G-Series GT2 / GT3.....	7
4. Installation & mounting	8
4.1 Magnet installation.....	8
4.2 Mounting dimensions of G-Series.....	9
4.3 Multi-position measurement distances.....	10
5. Electrical connections	11
5.1 Analog.....	11
5.2 Start/Stop.....	11

1. Introduction

1.1 Purpose and use of this manual

Before starting the operation of Temposonics® sensors read this documentation thoroughly and follow the safety information. Keep the manual for future reference!

The content of this technical documentation is intended to provide information on mounting, installation and commissioning by qualified automation personnel¹ or instructed service technicians who are familiar with the project planning and dealing with Temposonics® sensors.

1.2 Used symbols and warnings

Warnings are intended for your personal safety and for avoidance of damage to the described product or connected devices. In this documentation, safety information and warnings to avoid danger that might affect the life and health of operating or service personnel or cause material damage are highlighted by the preceding pictogram, which is defined below.

Symbol	Meaning
NOTICE	This symbol is used to point to situations that may lead to material damage, but not to personal injury.

- 1/ The term qualified technical personnel characterizes persons who:
- are familiar with the safety concepts of automation technology applicable to the particular project,
 - are competent in the field of electromagnetic compatibility (EMC) ,
 - have received adequate training for commissioning and service operations
 - are familiar with the operation of the device and know the information required for correct operation provided in the product documentation.

2. Safety instructions

2.1 Intended use


This product may be used only for the applications defined under item 1 only in conjunction with the third-party devices and components recommended or approved by MTS Sensors. As a prerequisite of proper and safe operation the product requires correct transport, storage, mounting and commissioning and must be operated with utmost care.

1. The sensor systems of all Temposonics® series are intended exclusively for measurement tasks encountered in industrial, commercial and laboratory applications. The sensors are considered as system accessories and must be connected to suitable evaluation electronics, e.g. a PLC, IPC, indicator or other electronic control unit.


2.2 Foreseeable misuse

Foreseeable misuse	Consequence
Wrong sensor connection	The sensor does not work properly or will be destroyed
Operate the sensor out off the operating temperature	No signal output The sensor can be damaged
Power supply is out of the defined range	Signal output is wrong / no signal output / the sensor will be damaged
Position measurement is influenced by an external magnetic field	Signal output is wrong
Cables are damaged	Short circuit – the sensor can be destroyed / sensor does not respond
Spacers are missing / are installed in a wrong order	Error in position measurement
Wrong connection of ground / shield	Signal output is disturbed The electronics can be damaged
Use of a magnet that is not certified by MTS Sensors	Error in position measurement

Do not reprocess the sensor afterwards.
→ The sensor might be damaged.



Do not step on the sensor.
→ The sensor might be damaged.



2.3 Installation, commissioning and operation

The position sensors must be used only in technically safe condition. To maintain this condition and to ensure safe operation, installation, connection and service, work may be performed only by qualified technical personnel.

If danger of injury to persons or of damage to operating equipment is caused by sensor failure or malfunction, additional safety measures such as plausibility checks, limit switches, EMERGENCY STOP systems, protective devices etc. are required. In the event of trouble, shut down the sensor and protect it against accidental operation.

Safety instructions for commissioning

To maintain the sensor's operability, it is mandatory to follow the instructions given below.

1. Protect the sensor against mechanical damage during installation and operation.
2. Do not open or dismantle the sensor.
3. Connect the sensor very carefully and pay attention to the polarity of connections and power supply.
4. Use only approved power supplies.
5. It is indispensable to ensure that the specified permissible limit values of the sensor for operating voltage, environmental conditions, etc. are met.
6. Check the Funktion of the sensor regularly and provide documentation of the checks.
7. Before system switch-on, ensure that nobody's safety is jeopardized by starting machines.

2.4 Safety instructions for use in explosion-hazardous areas

The sensors are not suitable for operation in explosion-hazardous areas.

2.5 Warranty

MTS Sensors grants a warranty² period for the Temposonics® position sensors and supplied accessories relating to material defects and faults that occur despite correct use in accordance with the intended application. The MTS Sensors obligation is limited to repair or replacement of any defective part of the unit. No warranty can be provided for defects that are due to improper use or above average stress of the product, as well as for wear parts. Under no circumstances will MTS Sensors accept liability in the event of offense against the warranty rules, no matter if these have been assured or expected, even in case of fault or negligence of the company.

MTS Sensors explicitly excludes any further warranties. Neither the company's representatives, agents, dealers nor employees are authorized to increase or change the scope of warranty.

2.6 Return

For diagnostic purposes, the sensor can be returned to MTS Sensor Technologie GmbH & Co. KG. Any shipment cost is the responsibility of the sender². For a corresponding form, see detailed operation manual (available at: www.mtssensors.com).

2.7 Maintenance & removal

Maintenance

The sensor is maintenance-free.

Repair

Repairs on the sensor may be performed only by MTS Sensors or a repair facility explicitly authorized by MTS Sensors.

List of spare parts

No spare parts are available for this sensor.

Transport and storage

The conditions of transport and storage of the sensor match the operating conditions mentioned in this document.

Removal from service / dismantling

The product contains electronic components and must be disposed of in accordance with the local regulations.


^{2/} See also applicable MTS Sensors sales and supply conditions, e.g. at www.mtssensors.com

Temposonics® G-Series

Brief Instructions

3. Identification


Nameplate (e.g. G-Series GP Analog)



Approvals and certificates

You will find approvals and certificates in the sensor specific operation manuals.


3.1 Temposonics® G-Series GP (profile sensor)



Available outputs:

- Analog
- Start/Stop

3.2 Temposonics® G-Series GH (rod sensor)




Available outputs:

- Analog
- Start/Stop

Manuals & Software available at:
www.mtsensors.com

3.3 Temposonics® G-Series GT2/GT3 (rod sensor with redundant electronics)




Available output:


- Analog

4. Installation & mounting


4.1 Magnet installation

Typical use of magnets

 **For: GH & GT2/GT3**
 • Rotationally symmetrical magnetic field
Ring magnet

 **For: GH, GT2/GT3 & GP**
 • The magnet can be lifted off
 • Height tolerances can be compensated
U-magnet

 **For: GH & GP**
 • The magnet can be lifted off
 • Height tolerances can be compensated
Block magnet

 **For: GP**
 • The magnet is guided through the profile
 • The distance between the magnet and the waveguide is strictly defined
 • Easy coupling via the ball joint
Magnet slider


Install the magnet using non-magnetic material for mounting device, screws, spacers etc.. The magnet must not grind on the sensor rod. Alignment errors are compensated via the air gap.

- Max. permissible surface pressure: 40 N/mm² (only for ring magnets and U-magnets)
- Fastening torque for M4 screws: 1 Nm; use washers, if necessary
- Minimum distance between position magnet and any magnetic material has to be 15 mm.
- If no other option exists and magnetic material is used, observe the specified dimensions

NOTICE


Mount the ring magnet and U-magnet concentrically. Mount the block magnet centrally. The maximum permissible air gap must not be exceeded.

Concentric mounting of U-magnet




- 1 U-magnet
- 2 Non-magnetic mounting device and screws

Centered mounting of block magnet



- 1 Block magnet
- 2 Non-magnetic mounting device and screws

Magnet mounting with magnetic material



- 1 Null zone, depends on sensor model
- 2 Distance between position magnet and any magnetic material (≥ 15 mm)
- 3 Non-magnetic spacer (≥ 5 mm) – Recommendation: 8 mm

Magnet mounting with magnetic material


- A. If the position magnet aligns with the drilled piston rod
- B. If the position magnet is set further into the drilled piston rod, install another non-magnetic spacer above the magnet

Notice for sensors with stroke lengths ≥ 1 meter


Support horizontally installed sensors with a stroke length from 1 meter mechanically at the rod end. Without the use of a support, rod and position magnet may be damaged. A false measurement is also possible. Longer rods require evenly distributed mechanical support over the entire length. Use an U-magnet for measurement.

4.2 Mounting dimensions of G-Series


G-Series GP with U-magnet




G-Series GP with magnet slider »S«, »N«, »V«, »G«




G-Series GP with block magnet




G-Series GH with U- / ring-magnet



G-Series GH with block magnet



G-Series GT2 / GT3 with U- / ring-magnet



Manuals & Software available at:
www.mtssensors.com

All dimensions in mm






Temposonics® G-Series

Brief Instructions

4.3 Multi-position measurement distances

Multi-position measurement with G-Series GP / GH sensors and Start / Stop output is possible, with a simultaneous measuring up to 9 positions

The stroke length influences the maximum number of magnets. Note the minimum distance between the magnets.

G-Series GP with U-magnet	G-Series GP with magnet slider »S«, »N«, »V«, »G«
	
G-Series GP with block magnet	G-Series GH with ring- / U-magnet
	
G-Series GH with block magnet	NOTICE Use only the same magnet type for multi-position measurement!
	

All dimensions in mm

Manuals & Software available at:
www.mtssensors.com

5. Electrical connections

Placement of installation and cabling have decisive influence on the sensor's electromagnetic compatibility (EMC). Hence correct installation of this active electronic system and the EMC of the entire system must be ensured by using suitable metal connectors, shielded cables and grounding. Overvoltages or faulty connections can damage its electronics despite protection against wrong polarity.

NOTICE

Never connect / disconnect the sensor when voltage is applied.

Instructions for connection

- Use low-resistant twisted pair and shielded cables and connect the shield to ground externally via the controller equipment.
- Keep control and sign leads separate from power cables and sufficiently far away from motor cables, frequency inverters, valve lines, relays, etc.
- Use only connectors with metal housing and connect the shielding to the connector housing.
- Keep the connection surface at both shielding ends as large as possible.
- Keep all non-shielded leads as short as possible.
- Keep the earth connection as short as possible with a large cross section. Avoid ground loops.
- With potential differences between machine and electronics earth connections, no compensating currents are allowed to flow across the cable shielding.

Recommendation:



Install potential compensating leads with large cross section, or use cables with separate double shielding, and connect only one end of the shield.

- Use only stabilized power supplies in compliance with the specified connecting values.

NOTICE

Do not mount the sensors in an area of strong magnetic or electric noise fields.
Sensors must be grounded via ground lug on the sensor electronics housing.

Sensor grounding



5.1 Analog

D60 / HXX / RXX

M16 connector	Pin	Cable	Function
	1	GY	Position
	2	PK	DC Ground
	3	YE	USB programmer
	4	GN	USB programmer
	5	BN	+24 VDC (-15 / 20 %)
	6	WH	DC Ground (0 V)

LED status

Green	Red		
		ON	OFF Normal function
		ON	ON Magnet not detected
		Flashing	OFF Serial programming mode

5.2 Start/Stop

D60 / RXX / HXX

M16 connector	Output	Pin	Cable	Function
	1	1	GY	Stop (-)
		2	PK	Stop (+)
	2	3	YE	Start (+)
		4	GN	Start (-)
		5	BN	+24 VDC (-15 / 20 %)
		6	WH	DC Ground (0 V)

LED status

Green	Red		
		ON	OFF Normal function
		ON	Flashing Missing external start signal
		ON	ON Magnet not detected
		Flashing	OFF Serial programming mode

Manuals & Software available at:
www.mtssensors.com

Document Part Number:
551515 Revision D (EN) 06/2016

LOCATIONS

USA

**MTS Systems Corporation
Sensors Division**
3001 Sheldon Drive
Cary, N.C. 27513, USA
Tel. +1 919 677-0100
Fax +1 919 677-0200
info.us@mtssensors.com
www.mtssensors.com

JAPAN

MTS Sensors Technology Corp.
737 Aihara-machi,
Machida-shi,
Tokyo 194-0211, Japan
Tel. +81 42 775-3838
Fax +81 42 775-5512
info.jp@mtssensors.com
www.mtssensors.com

FRANCE

MTS Systems SAS
Zone EUROPARC Bâtiment EXA 16
16/18, rue Eugène Dupuis
94046 Creteil, Frankreich
Tel. +33 1 58 4390-28
Fax +33 1 58 4390-03
info.fr@mtssensors.com
www.mtssensors.com

GERMANY

**MTS Sensor Technologie
GmbH & Co. KG**
Auf dem Schüffel 9
58513 Lüdenscheid, Germany
Tel. +49 2351 9587-0
Fax +49 2351 56491
info.de@mtssensors.com
www.mtssensors.com

CHINA

MTS Sensors
Room 504, Huajing Commercial Center,
No. 188, North Qinzhou Road
200233 Shanghai, China
Tel. +86 21 6485 5800
Fax +86 21 6495 6329
info.cn@mtssensors.com
www.mtssensors.com

ITALY

**MTS Systems Srl
Sensor Division**
Via Camillo Golgi, 5/7
25064 Gussago (BS), Italy
Tel. +39 030 988 3819
Fax +39 030 982 3359
info.it@mtssensors.com
www.mtssensors.com

LEGAL NOTICES

MTS, Temposonics and Level Plus are registered trademarks of MTS Systems Corporation in the United States; MTS SENSORS and the MTS SENSORS logo are trademarks of MTS Systems Corporation within the United States. These trademarks may be protected in other countries. All other trademarks are the property of their respective owners. Copyright © 2016 MTS Systems Corporation. No license of any intellectual property rights is granted. MTS reserves the right to change the information within this document, change product designs, or withdraw products from availability for purchase without notice. Typographic and graphics errors or omissions are unintentional and subject to correction. Visit www.mtssensors.com for the latest product information.



Reg.-No. 003095-QM08