

## **Temposonics**®

Magnetostrictive Linear Position Sensors

## MH-Series MH Threaded Analog Data Sheet

- Stroke length up to 2500 mm
- With M18×1.5 thread
- Sensor rod with Ø 7 mm or Ø 10 mm
- Rugged to withstand off-highway shock and vibration



Data Sheet

#### **MEASURING TECHNOLOGY**

The absolute, linear position sensors provided by MTS Sensors rely on the company's proprietary Temposonics® magnetostrictive technology, which can determine position with a high level of precision and robustness. Each Temposonics® position sensor consists of a ferromagnetic waveguide, a position magnet, a strain pulse converter and supporting electronics. The magnet, connected to the object in motion in the application, generates a magnetic field at its location on the waveguide. A short current pulse is applied to the waveguide. This creates a momentary radial magnetic field and torsional strain on the waveguide. The momentary interaction of the magnetic fields releases a torsional strain pulse that propagates the length of the waveguide. When the ultrasonic wave reaches the end of the waveguide it is converted into an electrical signal. Since the speed of the ultrasonic wave in the waveguide is precisely known, the time required to receive the return signal can be converted into a linear position measurement with both high accuracy and repeatability.




Fig. 1: Time-of-flight based magnetostrictive position sensing principle

#### MH THREADED SENSOR

The Temposonics® MH-Series sensors are specifically designed for direct stroke measurement in hydraulic cylinders. The MH Threaded sensor extends the rugged design of the Temposonics® MH Series sensors to external threaded installations. A MTS M12 connector system ensures protection to IP69K. The inherent absolute capabilities ensure that the MH Threaded sensor is always ready. With two connections styles, the responsive magnetostrictive linear position sensors can be integrated into most installations.

Temposonics® MH Threaded sensors can be used in applications where access is available from the outside of the cylinder. Example applications include lift and tilt cylinders, hydraulic jacks, and hydraulic steering systems in agricultural and construction machinery.




Fig. 2: Typical application: Agricultural sprayer


#### **TECHNICAL DATA**

Output		
Current	420 mA	
Voltage	0.254.75 VDC; 0.54.5 VDC	
Measured value	Position	
Signal characteristic	Analog output restricted by noise and ADC	
Measurement parameters		
Resolution	Typ. 0.1 mm	
Internal sample rate	2 ms	
Linearity	$00500250 \text{ mm} \le \pm 0.1 \text{ mm}$ $02552000 \text{ mm} \pm 0.04 \% \text{ (F.S.)}$ $20052500 \text{ mm} \le \pm 0.8 \text{ mm}$	
Hysteresis	±0.1 mm	
Setpoint tolerance	< 1 mm	
Operating conditions		
Mounting position	Any	
Operating temperature	–40+85 °C	
Storage temperature	−25…+65 °C	
Humidity	EN60068-2-30, 90 % rel. humidity, no conden	sation
Ingress protection – M12 connector	IP69K with M12 connector and mating plug	
Ingress protection – Cable output	IP69K	
Shock test	IEC 60068-2-27, 100 g (6 ms) single shock, 5	0 g (11 ms) at 1000 shocks per axis
Vibration test	Vibrations: IEC 60068-2-64, 15 g (r.m.s.) Ø 7 mm rod (102000 Hz) - res 20 g (r.m.s.) Ø 10 mm rod (102000 Hz) - re	
EMC test	2009/64/EG Road vehicles 2009/19/EG Agricultural and Forest machines ISO 14982 Emissions/Immunity ISO 7637-1/2 Transient Impulses ISO / TR 10605 Electrostatic Discharge (E.S.I	
Pressure impulse test according DIN EN ISO 19879	Ø 7 mm rod	Ø 10 mm rod
Operation pressure (P <sub>N</sub> )	300 bar	350 bar
Operation pressure (P <sub>max</sub> )	400 bar	450 bar
Operation pressure (P <sub>static</sub> )	525 bar	625 bar
Design/Material		
Sensor electronics housing	Stainless steel 1.4305 (AISI 303)	
Sensor rod	Ø 7 mm: Stainless steel 1.4301 (AISI 304) / Ø	10 mm: Stainless steel 1.4306 (AISI 304L)
Stroke length	502500 mm	,
Sealing	O-ring 15.4 × 2.1, NBR 90 black	
Electrical connection		
Connection type	M12 connector or cable output	
Operating voltage	+12/24 VDC (832 VDC)	
Current consumption	12 VDC: typ. < 100 mA; 24 VDC: typ. < 50 mA	
Load (output VDC)	$R_i \ge 10 \text{ k}\Omega$	
Loud (output mA)	12 VDC: $R_1 \le 250 \Omega$ ; 24 VDC: $R_1 \le 500 \Omega$	
Inrush current	12 VDC: max. 2.5 A/2 ms; 24 VDC: max. 4.5	A/2 ms
Supply voltage ripple	< 1 % pp	
Power drain	< 1 W	
Over voltage protection (VDC-GND)	Up to +36 VDC	
Polarity protection (GND-VDC)	Up to -36 VDC	
Electric strength	500 VDC (DC GND to chassis GND)	
	TOTAL TO (DO GITE TO SINGOIO GITE)	

#### **TECHNICAL DRAWING**




#### **TECHNICAL DRAWING**



#### **CONNECTOR WIRING**

M12 connector					Cable	output
	Pin	Е	G	Н	Color	
$\frac{3}{3}$	1	not connected	VDC	VDC	BN	VDC
(((((((((((((((((((((((((((((((((((((((	2	VDC	not connected	SIG	WH	GND
1 2	3	GND	GND	GND	GN	SIG
	4	SIG	SIG	not connected	-	-

#### FREQUENTLY ORDERED ACCESSORIES





#### **INSTALLATION**

#### **Hydraulics sealing**

For sealing the flange contact surface, a sealing via an O-ring  $15.3 \times 2.2$  mm in the undercut is necessary. A screw hole based on ISO 6149-1 must be provided.

#### Screw hole based on ISO 6149-1






- Note the fastening torque of 50 Nm.
- The flange contact surface must be seated completely on the cylinder mounting surface.
- The cylinder manufacturer determines the pressure-resistant gasket (copper gasket, O-ring, etc.).
- The position magnet should not make contact with the sensor rod.
- The peak pressure should not be exceeded.
- · Protect the sensor rod against wear.

#### For In-Cylinder installation:


- The plunger borehole:
  - Ø 7 mm rod: ≥ Ø 10 mm
  - Ø 10 mm rod: ≥ Ø 13 mm
  - depends on the pressure and piston speed.
- The bore depth in piston:

Null zone + Stroke length + Dead zone + > 3 mm

#### Magnet installation for In-Cylinder applications



#### Magnet installation for float applications



#### **ORDER CODE**



#### a Sensor model

M H Rod

#### b Form factor

- G Threaded port M18×1.5, rod Ø 10 mm, M8 plug (male)
- K Threaded port M18×1.5, rod Ø 10 mm, M6 plug (female)
- Threaded port M18×1.5, rod Ø 7 mm, flat plug
- T Threaded port M18×1.5, rod Ø 10 mm, flat plug

#### c Stroke range (mm)

0050...2500 mm (in 5 mm steps)

#### d Electrical wiring

#### M12 connector (VDC - GND - SIG)

M	0	0	Ε	4 pin (2-3-4)
M	0	0	G	4 pin (1-3-4)
М	0	0	Н	4 pin (1-3-2)

#### Cable output

C	0	3	A	300 mm pigtailed wire termination
C	0	5	A	500 mm pigtailed wire termination
C	1	0	A	1000 mm pigtailed wire termination
C	2	0	A	2000 mm pigtailed wire termination
C	3	0	A	3000 mm pigtailed wire termination
C	5	0	A	5000 mm pigtailed wire termination

#### e Supply voltage

3 +12/24 VDC (8...32 VDC)

#### f Output

٧	1	1	0.254.75 VDC
٧	1	2	0.54.5 VDC
V	1	3	4.750.25 VDC
٧	1	4	4.50.5 VDC
Α	0	1	420 mA
Α	0	4	204 mA

#### **DELIVERY**



Accessories have to be ordered separately.

Operation manuals & software are available at: www.mtssensors.com



#### **Document Part Number:**

551827 Revision A (EN) 01/2017

## OCATIONS

#### USA MTS Systems Corporation Sensors Division 3001 Sheldon Drive Cary, N.C. 27513, USA

Cary, N.C. 27513, USA Tel. +1 919 677-0100 Fax +1 919 677-0200 info.us@mtssensors.com www.mtssensors.com

#### JAPAN MTS Sensors Technology Corp.

737 Aihara-machi, Machida-shi, Tokyo 194-0211, Japan Tel. +81 42 775-3838 Fax +81 42 775-5512 info.jp@mtssensors.com www.mtssensors.com

#### FRANCE

MTS Systems SAS Zone EUROPARC Bâtiment EXA 16

16/18, rue Eugène Dupuis 94046 Creteil, France Tel. +33 1 58 4390-28 Fax +33 1 58 4390-03 info.fr@mtssensors.com

www.mtssensors.com

#### GERMANY

#### MTS Sensor Technologie GmbH & Co. KG Auf dem Schüffel 9

58513 Lüdenscheid, Germany Tel. +49 2351 9587-0 Fax +49 2351 56491 info.de@mtssensors.com www.mtssensors.com

#### CHINA MTS Sansara

#### MTS Sensors

Room 504, Huajing Commercial Center, No. 188, North Qinzhou Road 200233 Shanghai, China Tel. +86 21 6485 5800 Fax +86 21 6495 6329 info.cn@mtssensors.com www.mtssensors.com

#### ITALY MTS S

MTS Systems Srl Sensor Division

Via Camillo Golgi, 5/7 25064 Gussago (BS), Italy Tel. +39 030 988 3819 Fax +39 030 982 3359 info.it@mtssensors.com

# **EGAL NOTICES**

MTS, Temposonics and Level Plus are registered trademarks of MTS Systems Corporation in the United States; MTS SENSORS and the MTS SENSORS logo are trademarks of MTS Systems Corporation within the United States. These trademarks may be protected in other countries. All other trademarks are the property of their respective owners. Copyright © 2017 MTS Systems Corporation. No license of any intellectual property rights is granted. MTS reserves the right to change the information within this document, change product designs, or withdraw products from availability for purchase without notice. Typographic and graphics errors or omissions are unintentional and subject to correction. Visit www.mtssensors.com for the latest product information.



